

We Claim:

1. A transceiver configuration for a communication terminal, comprising:

an A/D converter outputting a first digital data signal;

a D/A converter;

a controllable oscillator circuit connected to said A/D converter and to said D/A converter, said controllable oscialloctor circuit having a reference oscillator with an oscillating crystal as a resonator and outputs a sampling clock received by said A/D converter and said D/A converter;

a digital data processing circuit connected to said A/D converter and to said D/A converter and receives the first digital data signal output by said A/D converter and processes it further and outputs a second digital data signal to said D/A converter, and said A/D converter, said D/A converter, said data processing circuit and said controllable oscillator circuit, apart from said oscillating crystal of said reference oscillator, being constructed as a monolithically integrated circuit so that of said controllable oscillator circuit, only said oscillating crystal is implemented as an external component; and

a frequency section being at least one of a radio-frequency section and an intermediate-frequency section connected to said A/D converter, to said D/A converter and to said controllable oscillator circuit, said frequency section having a frequency converter stage operating with a beat frequency derived from said controllable oscillator circuit.

2. The transceiver configuration according to claim 1, wherein said digital data processing circuit has a digital filter and a digital modulator.

3. The transceiver configuration according to claim 1, wherein said digital data processing circuit has a channel estimator.

4. The transceiver configuration according to claim 3, including a data detector connected to said channel estimator.